

System	Recommended Applications			Nominal Voltage (V)	Average Service Capacity (mAh)	maxell	EVE-READY	DURA-CELL	RAY-O-VAC	SEIKO	CITIZEN	TIMEX	VARTA	RENA-TA	BUL-OVA	IEC	
		Millimeters φ × ht.	Inches φ × ht.														
Silver Oxide Battery	Watch High Drain 	11.6 × 5.4	0.457 × 0.213	1.55	165	SR44W	357	D357	RW42	SB-B9	—	J	V357	357	228	SR44	
		11.6 × 4.2	0.457 × 0.165	1.55	125	SR43W	386	D386	RW44	SB-B8	280-41	H	V386	386	260	SR43	
		11.6 × 3.05	0.457 × 0.120	1.55	80	SR1130W	389	D389	RW49	SB-BU	280-15	M	V389	389	603	SR54	
		11.6 × 2.05	0.457 × 0.081	1.55	55	SR1120W	391	D391	RW40	SB-BS	280-30	L	V391	391	609	SR55	
		9.5 × 2.73	0.374 × 0.107	1.55	55	SR927W	399	D399	RW413	SB-BP	280-44	—	V399	399	613	SR57	
		9.5 × 2.05	0.374 × 0.081	1.55	39	SR920W	370	—	RW415	SB-BN	280-51	Z	—	—	370	—	
		7.9 × 5.4	0.311 × 0.213	1.55	75	SR754W	393	D393	RW48	SB-B3	—	—	F	V393	393	255	SR48
		7.9 × 3.6	0.311 × 0.142	1.55	39	SR41W	392	D392	RW47	SB-B1	280-13	K	V392	392	247B	SR41	
		7.9 × 2.6	0.311 × 0.102	1.55	28	SR726W	396	D396	RW411	SB-BL	280-52	V	V396	396	612	SR59	
		7.9 × 2.15	0.311 × 0.085	1.55	25	SR721W	361	D361	RW410	SB-BK	280-53	X	—	—	361	—	SR58
		6.8 × 2.6	0.268 × 0.103	1.55	26	SR626W	—	—	—	SB-BW	—	—	—	—	—	—	—
		6.8 × 2.15	0.268 × 0.085	1.55	18	SR621W	—	—	—	—	—	—	—	—	—	—	—
		*1 9.5 × 2.73	0.374 × 0.107	1.55	44	XR9527W	—	—	—	—	XR9527W	—	—	—	—	48	—
		*1 11.6 × 3.05	0.457 × 0.120	1.55	76	XR11630W	—	—	—	—	XR11630W	—	—	—	—	—	—
		Watch Low Drain 	11.6 × 5.4	0.457 × 0.213	1.55	165	SR44SW	303	D303	RW32	SB-A9	280-08	A	V303	303	—	SR44
			11.6 × 4.2	0.457 × 0.165	1.55	110	SR43SW	301	D301	RW34	SB-A8	280-01	D	V301	301	226	SR43
			11.6 × 3.05	0.457 × 0.120	1.55	82	SR1130SW	390	D390	RW39	SB-AU	280-24	—	V390	390	603	SR54
			11.6 × 2.05	0.457 × 0.081	1.55	55	SR1120SW	381	D381	RW30	SB-AS	280-27	—	V381	381	317	SR55
	11.6 × 1.65		0.457 × 0.065	1.55	29	SR1116SW	366	D366	RW318	—	280-46	—	—	—	608	—	
	9.5 × 3.6		0.374 × 0.142	1.55	70	SR936SW	394	D394	RW33	SB-A4	280-17	—	V394	394	—	SR45	
	9.5 × 2.73		0.374 × 0.107	1.55	55	SR927SW	395	D395	RW313	SB-AP	280-48	—	V395	395	610	SR57	
	9.5 × 2.05		0.374 × 0.081	1.55	39	SR920SW	371	D371	RW315	SB-AN	280-31	—	V371	371	605	—	
	9.5 × 1.65		0.374 × 0.065	1.55	26.5	SR916SW	373	D373	RW317	SB-AJ	280-45	—	V373	373	—	—	
	7.9 × 3.6		0.311 × 0.142	1.55	45	SR41SW	384	D384	RW37	SB-A1	280-18	—	V384	384	247	SR41	
	7.9 × 2.6		0.311 × 0.102	1.55	33	SR726SW	397	D397	RW311	SB-AL	280-28	W	V397	397	607	SR59	
	7.9 × 2.15		0.311 × 0.085	1.55	25	SR721SW	362	D362	RW310	SB-AK	280-29	S	V362	362	601	SR58	
	7.9 × 1.68		0.311 × 0.066	1.55	19	SR716SW	315	D315	RW316	—	280-56	—	V315	315	—	—	
	7.9 × 1.29		0.311 × 0.050	1.55	10	SR712SW	—	—	—	—	—	—	—	—	—	—	
	6.8 × 2.6		0.268 × 0.102	1.55	26	SR626SW	377	D377	RW329	SB-AW	280-39	—	V377	377	—	—	
	6.8 × 2.15		0.268 × 0.085	1.55	18	SR621SW	364	D364	RW320	SB-AG	280-34	T	V364	364	602	SR60	
	6.8 × 1.65		0.268 × 0.065	1.55	14	SR616SW	321	D321	RW321	SB-AF	—	—	V321	321	611	—	
	5.8 × 2.73		0.228 × 0.107	1.55	16	SR527SW	319	D319	RW328	SB-AE	280-60	—	—	—	—	—	
	5.8 × 2.15		0.228 × 0.085	1.55	14	SR521SW	379	D379	RW327	SB-AC	208-59	—	V379	379	—	—	
	5.8 × 1.65		0.228 × 0.065	1.55	10	SR516SW	317	D317	—	SB-AR	280-58	—	V317	—	—	—	
	5.8 × 1.25	0.228 × 0.049	1.55	5	SR512SW	335	—	—	SB-AB	—	—	—	—	—	—		
	5.8 × 1.08	0.228 × 0.043	1.55	4.3	SR510SW	—	—	—	—	—	—	—	—	—	—		
General 	11.6 × 5.4	0.457 × 0.213	1.55	165	SR44(G13)	S76	MS76	RS76	—	—	—	—	V76HS	—	—	SR44	
	11.6 × 4.2	0.457 × 0.165	1.55	125	SR43(G12)	S41	MS41	RS41	—	—	—	—	V41HS	17	—	SR43	
	11.6 × 3.05	0.457 × 0.120	1.55	80	SR1130	389	—	—	—	—	—	—	V10GS	—	—	SR54	
	11.6 × 2.05	0.457 × 0.081	1.55	55	SR1120	291	—	—	—	—	—	—	V8GS	—	—	SR55	
	13.0 × 25.2	0.512 × 0.992	6.2	165	45R44(4G13)	544	RX28	BPX28	—	—	—	—	V28PX	—	—	4SR44	
	Micro Alkaline Battery 	*2 11.6 × 5.4	0.457 × 0.213	1.5	80	LR44	A76	LR44	RW82	76A	BLR44	—	V13GA	—	—	LR44	
		*2 11.6 × 4.2	0.457 × 0.165	1.5	65	LR43	186	LR43	RW84	86A	BLR43	—	V12GA	—	—	LR43	
		11.6 × 3.05	0.457 × 0.120	1.5	47	LR1130	189	LR54	RW89	89A	BLR54	—	V10GA	—	—	LR54	
		11.6 × 2.05	0.457 × 0.081	1.5	25	LR1120	191	LR55	—	91A	—	—	V8GA	—	—	LR55	
		9.5 × 3.6	0.374 × 0.142	1.5	44	LR936	—	—	—	SB-F4	—	—	—	—	—	LR45	
7.9 × 3.6		0.311 × 0.142	1.5	23	LR41	192	—	—	—	—	—	V3GA	—	—	LR41		
7.9 × 2.6		0.311 × 0.102	1.5	21	LR726	—	—	—	—	—	—	—	—	—	—		
6.8 × 2.6		0.268 × 0.102	1.5	17	LR626	—	—	—	—	—	—	—	—	—	—		
13.0 × 25.2		0.512 × 0.992	6.0	80	4LR44	A544	—	—	—	—	B4LR44	—	V4034PX	—	—	4LR44	
Lithium Manganese Dioxide Battery General Memory Back Up 		20.0 × 3.2	0.787 × 0.126	3.0	200	CR2032	E-CR2032	DL2032	CR2032	—	—	—	—	CR2032	—	—	—
	20.0 × 2.5	0.787 × 0.098	3.0	140	CR2025	E-CR2025	DL2025	CR2025	—	—	—	—	CR2025	—	—	—	
	20.0 × 1.6	0.787 × 0.063	3.0	70	CR2016	E-CR2016	DL2016	—	SB-T11	280-204	—	—	CR2016	—	—	—	
	12.5 × 2.0	0.492 × 0.079	3.0	36	CR1220	—	—	—	—	—	—	—	CR1220	—	—	—	